SC12-30
Twelve Channel Amplifier



Fully Configurable Power Amp. Multivoltge

The Nice SC12-30 Offers the classic power and stability that you've come to know and trust. The Nice SC12-30 is specifically designed to solve the problem of interfacing with different brands and models of equipment and different rooms and application. Nice SC12-30 makes installation easier and more straight forward than ever before.

12-Channel Amplifier

The Nice SC2-100 Amplifier provides 30W per channel (80W when bridged) and our unique BusMatrix™ Selector. Nice SC12-30 is perfect multi-zone or multi-room solution.

SPEAKERCRAFT
a Nice brand

SC12-30 Twelve Channel Amplifier



Features

- **Real World Power**
  Nice SC12-30 is a 12-channel amplifier that delivers a solid 30 watts per channel RMS into 8 Ohms and 40 watts per channel RMS into 4 Ohms
- **Turn-On Modes**
  The Nice SC2-100 Amplifier features three turn-on modes: Manual turn-on via the front panel switch, Audio Sense and External Voltage trigger
- **Twelve to Six channel Configurable Power**
  Each of the Nice SC12-30 six adjacent speaker output pairs are bridgeable. You can create up to six 80 watt channels by sliding the bridging switches located between each pair to the "bridged" position
- **BusMatrix™ Selector**
  Our unique BusMatrix Selector gives you the flexibility to assign each channel to a common Left, Right or Mono signal bus, or to a dedicated signal input. With the BusMatrix routing surround sound to the master's bedroom, stereo to the den and mono to the powder room is as simple as flicking a switch
- **Freedom from Noise and Cross-talk**
  The Nice SC12-30 BusMatrix incorporates advanced PCB construction ensuring extremely high channel to channel isolation, Signal to noise ratios and cross-talk are equivalent to a professional mixing board found in a recording studio

Specifications

Power Consumption	30 watts RMS per channel into 8 Ohms (all channels driven) 40 watts RMS per channel into 4 Ohms (all channels driven) Adjacent channels are bridgeable to 80 watts RMS into 8 Ohms (all channels driven)
Total Harmonic Distortion	0.2% THD from 20Hz to 20kHz
Voltage trigger input	Accepts 3-24 VAC / DC
Control out	12V
Line cord	Removable
Warranty	2-year warranty
Weight	35 lbs (15.8 kg)

Certification	Tested and Certified to US, Canada, EU and Australian safety and EMC Standards
Rack	Mount ears included
Dimensions	(in) 17.25 W x 15.25 D x 5.75 H (cm) 41.11W x 41.11 D x 16.25 H (Including feet)
Number of Channels	12
Watts RSM Per Channel	30
Shipping Info	Length: 23.1" Width: 19.3" Height: 10.1" Weight: 40.05 lbs Unit of Measure: Each UPC: 664254999680
Master Park Qty	2

Niceforyou.com

©2023 Nice North America LLC. All rights reserved.
All other products or name brands are trademarks of their respective holders.